## JÖRGENSEN ••



COMMUNICATION:

868 MHz, 2-way Range: 100 meters

## TRANSMITTER:

6 x Function-buttons 2 x Start-buttons, with function 1 x Stop-button 3-Step battery indicator 2 x AA battery IP class: IP67 Weight: 135 g Size: 112 x 62 x 39 mm

## **RECIEVER:**

8 x NC/NO Relay 10-42 VDC Relay max 20 Ampere IP class: IP66 Weight: ~500g Size: 130 x 146 x 57 mm

Cables are included according to picture to the right.

## **ROBUST RADIOSYSTEM SIGNUM**

The SIGNUM radiosystem is designed for tough environments, such as TRUCKS, TOWERS, FORESTRY and VINCH. The system can be used for industsrial applications as well, such as PORT-CONTROL.

SIGNUM radio ha 8 relay outputs to control functions. Apart from these relays, an extra one exists thats activated as soon as the radio is connected to the reciever. This relay can then be used for the dump valve on a hydraulic system. The system can be made even more reliable if the transmitter is replaced with physical buttons on the reciever instead. This guarantees that the machine wont be left standing if the transmitter was lost or the battery was completely dead.

Another feature is that the transmitter can be password-protected. The recievers functions are customizable. The system utilizes ACS (Auto Channel Selection).

The reciever comes with complete cabling for quick installation.



